Viking FXI-1A FXO/FXS/Telecom Smart Paging Interface

SL-FXI-1A VIKING

Interface that connects a paging amplifier to a phone system through an FXS port/ATA, an FXO trunk port, or a PBX paging port. It provides talk battery, VOX and page time-outs and a relay to key the amplifier. We use it to tie existing overhead paging amps into hosted VoIP systems.





ELECTRICAL

Power	120 VAC / 12 VDC 500 mA UL listed adapter included (not required in FXS mode)
Talk battery	30 VDC
Relay contacts	1 A @ 30 VDC / 0.5 A @ 125 VAC, 250 VAC maximum
Connections	(10) cage clamp screw terminals

AUDIO & TIMING

VOX activation (normal)	-28 dBm minimum @ 1 kHz
VOX activation (lower sensitivity)	-25 dBm minimum @ 1 kHz
VOX time-out disconnect	2.5 to 10 s or disabled
Page time-out disconnect	5 to 60 s or disabled

PHYSICAL

Dimensions	4.38 × 2.97 × 1.38 in (111 × 76 × 36 mm)
Shipping weight	1.06 lb (0.48 kg)

ENVIRONMENTAL

Operating temperature	32 to 90 F (0 to 32 C)
Humidity	5% to 95% non-condensing

COMPLIANCE

Certifications	FCC Part 68, FCC Part 15

Prepared by Smart Life, LLC. Specifications and product images are provided by the manufacturer as of October 28, 2026 and are subject to change without notice. Product names are trademarks of their respective owners.