# Bogen PCMSYS3 Pre-Assembled 3-Zone PCM2000 Paging System

**SL-PCMSYS3**

ACCESSORIES

Factory pre-assembled and tested PCM2000 system with telephone interface, central processor, one 3-zone paging module and the PCMPS2 power supply. We use it as the starting point for 1-3 zone telephone paging jobs; it expands with more PCM modules later.




## OVERVIEW

| | |
|---|---|
| **Includes** | PCMTIM telephone interface, PCMCPU central processor, PCMZPM 3-zone module, PCMPS2 power supply |
| **Zones** | 3 out of the box; expandable to 99 with more modules/satellites |
| **Zone groups** | Up to 32 programmable |

## AUDIO / PAGING

| | |
|---|---|
| **System power handling** | 250 W |
| **Speaker systems** | 70 V central-amplified or self-amplified (24 V) |
| **Self-amp capacity** | Up to 40 self-amplified speakers per zone module |
| **Override** | Emergency all-zone paging input |

## TELEPHONE / I/O

| | |
|---|---|
| **Telephone** | RJ11 and terminal blocks; loop/ground start trunks, paging ports, 90 V analog stations |
| **Relays** | Two C-form contacts |
| **Night ringer** | 90 V and contact closure |

## PHYSICAL / COMPLIANCE

| | |
|---|---|
| **Mounting** | Wall; optional RPK84/RPK88 rack kits |
| **Listings** | FCC Part 68 registered; UL60950 listed |

Prepared by Smart Life, LLC. Specifications and product images are provided by the manufacturer as of October 28, 2026 and are subject to change without notice. Product names are trademarks of their respective owners.