Viking PA-30 30 W Telecom Paging Amplifier

SL-PA-30 VIKING

30 W paging amplifier with loud-ringing and background-music features that connects to a phone system paging port or analog line. It drives 8-ohm speakers directly or 25 V/70 V speaker lines. We use it for small to mid-size offices and shops that need overhead paging off the phone system.





AUDIO

Paging output	30 W, powers up to (30) 8-ohm speakers or (50) 70 V or 25 V speakers
Talk battery	40 VDC
Features	Paging, loud ringing, background music

ELECTRICAL

Power	120 VAC / 15 VAC 2.2 A UL listed adapter provided
Connections	(1) 3.5 mm (1/8 in) audio jack, (1) 17-position screw terminal block

PHYSICAL

Dimensions	5.25 × 3.5 × 1.75 in (133 × 89 × 44 mm)

Shipping weight	3 lb (1.36 kg)

ENVIRONMENTAL

Environment	32 to 90 F (0 to 32 C), 5% to 95% non-condensing

Prepared by Smart Life, LLC. Specifications and product images are provided by the manufacturer as of October 28, 2026 and are subject to change without notice. Product names are trademarks of their respective owners.